

## INRUSH CURRENT RATING VALTAVALO E3 LED TUBES

The table below describes the maximum number of E3 LED tubes that can be installed for one B- and C-curve circuit breaker.

### INRUSH CURRENT RATING / E3 LED TUBES

Circuit breaker		LED tube power / max. number of LED tubes				
		25W	20W	15W	10W	8W
B-curve	10A	35	35	35	42	42
	16A	57	57	57	67	67
C-curve	10A	59	59	59	70	70
	16A	93	93	93	111	111